
NASA TECH BRIEF



NASA Tech Briefs are issued to summarize specific innovations derived from the U. S. space program and to encourage their commercial application. Copies are available to the public from the Clearinghouse for Federal Scientific and Technical Information, Springfield, Virginia 22151.

Solid State Circuit Switches AC Load



The problem:

To design a solid state circuit that will switch ac signals with peak amplitudes greater than 5 volts. Prior art devices have been able to control dc voltages only.

The solution:

A differential amplifier circuit that biases a switching transistor on and off by a 0.1 to 5.0 dc control voltage.

How it's done:

The circuit consists of a dual NPN transistor, Q_1 , a current source, Q_2 , and an ac switch, Q_3 . Resistors R_1 and R_2 are initially adjusted to obtain proper switching action and to control the ac gain of the switch. With no dc control voltage applied, the collectors of Q_1 will essentially be at the supply potential of 20 vdc causing the base and emitter of the switch Q_3 to be at this same potential. In this condition, Q_3 will not conduct and there will be no ac signal out.

(continued overleaf)

This document was prepared under the sponsorship of the National Aeronautics and Space Administration. Neither the United States Government nor any person acting on behalf of the United States

Government assumes any liability resulting from the use of the information contained in this document, or warrants that such use will be free from privately owned rights.

Applying a dc control voltage of 0.1 to 5.0 volts to the base of section 1 of Q_1 , causes that section to conduct more heavily than section 2. Thus, the collector of section 1 will be at a lower voltage than the collector of section 2, causing Q_3 to be forward biased to conduct and pass the ac signal.

Notes:

1. Transistor Q_2 provides a constant current source for Q_1 for more stable operation. Resistor R_1 determines the on/off sensitivity of Q_3 by unbalancing Q_1 . Resistor R_2 is the signal gain potentiometer and is adjusted for unity gain so that 1 volt of input signal produces 1 volt of output signal.

- 2. Output of this switch is flat within 3 db from 6 cycles to 21.5 kc using 1 mfd coupling capacitors.
- 3. Inquiries concerning this innovation may be directed to:

Technology Utilization Officer Jet Propulsion Laboratory 4800 Oak Grove Drive Pasadena, California 91103 Reference: B66-10465

Patent status:

No patent action is contemplated by NASA. Source: Carl P. Chapman and Donald R. Rupnik (JPL-798)